



• A serration ring made of zinc die cast is inserted into the lever body made of plastic. They also realize sufficient strength for fitting with metal thread serration.

- A rich variety of thread sizes from M3 to M12 are available.
- There are three types of combinations of thread part materials / surface treatments:

**LEM** — Made of steel / ferrosoferric oxide film (black)

LEME --Made of steel / electroless nickel plating

**LEMS** — Made of stainless steel

- **LEME** has electroless nickel plating applied to its thread part made of steel to enhance its corrosion
- There are three color variations for the lever part. They can be selected by the end symbol of the part number.

End Symbol 🚯	Lever Part Color
ВК	Matte black
SG	Matte silver
OR	Matte orange

Unit:mm

## **Dimensions**

to hexalobular sockets.

Thread part: made of steel / ferrosoferric oxide film LEME Thread part: made of steel / electroless nickel plating **LEMS** Thread part: stainless steel

Part Number	Part Number	Part Number	M (Coarse)		R	н	H'	h	S	D			Max.*1 load (N)	clamping	
			Nominal of Thread												(g)
LEM-3		LEMS-3	M3	0.5	45	35.5	39	24.5	4.2	13	10	18	9	0.95	15
LEM-4	LEME-4	LEMS-4	M4	0.7	45	35.5	39	24.5	4.2	13	10	18	21	1.7	15 - 16
LEM-5	LEME-5	LEMS-5	M5	0.8	45	35.5	39	24.5	4.2	13	10	18	42	2.7	16 - 20
LEM-6	LEME-6	LEMS-6	M6	1	45	35.5	39	24.5	4.2	13	10	18	70	3.8	16 - 22
LEM-6B		LEMS-6B	M6	1	63	46.3	50.3	31	6.5	17.5	13.5	24	50	3.8	35 - 44
LEM-8	LEME-8	LEMS-8	M8	1.25	63	46.3	50.3	31	6.5	17.5	13.5	24	120	7	38 - 53
LEM-8B		LEMS-8B	M8	1.25	78	55.4	59.4	36	8	21	16	26	100	7	61 - 82
LEM-10A			M10	1.5	63	46.3	50.3	31	6.5	17.5	13.5	24	240	11	43 - 84
LEM-10	LEME-10	LEMS-10	M10	1.5	78	55.4	59.4	36	8	21	16	26	200	11	65 - 96
LEM-12A			M12	1.75	78	55.4	59.4	36	8	21	16	26	350	16	75 - 113
LEM-12	LEME-12	LEMS-12	M12	1.75	92	66	70	43	11	25	19	28	290	16	112 - 149

\*1: About the definition of max. load / max. clamping force → P.xxxx



•	Material/Finish

• Matchat/ mish			♥ Rol	15
	LEM	LEME	LEMS	
Lever Part	Nylon 6 (Various Color)	Nylon 6 (Various Color)	Nylon 6 (Various Color)	
Thread Part	SUM22L Ferrosoferric Oxide Film (Black)	SUM22L Electroless Nickel Plating	SUS303	
Setscrew	Steel Ferrosoferric Oxide Film (Black)	Steel Electroless Nickel Plating	Stainless Steel	
Serration Ring (Insert)	Zinc Die Cast	Zinc Die Cast	Zinc Die Cast	
Spring	Stainless Steel Wire or SWPB	Stainless Steel Wire	Stainless Steel Wire	

LEM Thread part: made of steel / ferrosoferric oxide film LEME Thread part: made of steel / electroless nickel plating LEMS Thread part: stainless steel

LEM-3 LEM-4 LEM-6 LEM-6 LEM-8 LEM-10 LEM-12 LEM-6-4 LEM-6-6 LEM-6-6 LEM-8-8 LEM-12 LEM-12 LEM-12 LEM-12 LEM-12 LEM-13 LEM-14 LEM-15 LEM-15 LEM-15 LEM-16 LEM-16 LEM-16 LEM-17 LEM-17 LEM-18 LEM-18 LEM-19 LEM	Part Number	Lm (mm) <b>2</b>											
LEM-4 LEM-6 LEM-6B LEM-8B LEM-10A LEM-12A LEM-12 LEM-6-6 LEM-6-6 LEM-6-6 LEM-6-6 LEM-6-6 LEM-7-5 LEM-7-5 LEM-7-6 LEM-8-8 LEM-10	rait Number	6	8	10	12	16	20	25	32	40	50	63	80
LEM-5 LEM-6 LEM-6 LEM-8 LEM-8 LEM-10A LEM-12 LEM-12 LEM-5 LEM-6 LEM-6 LEM-6 LEM-7 LEM-7 LEM-7 LEM-7 LEM-8 LEM-8 LEM-8 LEM-9 LEM-10 LEM-9 LEM-10 LEM-1	LEM-3	•	•	•	•	•							
LEM-6 LEM-6B LEM-8 LEM-8B LEM-10A LEM-10 LEM-12A LEM-12 LEM-5 LEME-6 LEME-8 LEME-6 LEME-8 LEME-10 LEME-8 LEME-10 LEME-	LEM-4			•	•	•	•	•	•				
LEM-6B LEM-8 LEM-8B LEM-10A LEM-10 LEM-12A LEM-12 LEME-4 LEME-5 LEME-6 LEME-6 LEME-8 LEME-10 LEME-10 LEME-12 LEME-10 LEME-12 LEME-12 LEMS-3 LEMS-3 LEMS-4 LEMS-5 LEMS-6 LEMS-6 LEMS-6 LEMS-6 LEMS-6 LEMS-6 LEMS-6 LEMS-6 LEMS-8 LEMS-8 LEMS-8 LEMS-8 LEMS-8 LEMS-8 LEMS-8 LEMS-8	LEM-5				•	•	•	•	•	•	•		
LEM-8B LEM-10A LEM-10 LEM-12A LEM-5 LEME-6 LEME-8 LEME-10 LEME-10 LEME-12 LEME-12 LEMS-3 LEMS-5 LEMS-5 LEMS-6 LEMS-8 LEMS-8 LEMS-8 LEMS-8 LEMS-8 LEMS-8 LEMS-8	LEM-6				•	•	•	•	•	•	•		
LEM-8B	LEM-6B				•	•	•	•	•	•	•	•	
LEM-10A LEM-12A LEM-4 LEME-5 LEME-6 LEME-8 LEME-10 LEME-12 LEME-10 LEME-12 LEME-5 LEME-6 LEMS-3 LEMS-6 LEMS-6 LEMS-6 LEMS-6 LEMS-6 LEMS-6 LEMS-7 LEMS-6 LEMS-8 LEMS-8 LEMS-8 LEMS-8 LEMS-8 LEMS-10 LEMS-8 LEMS-8 LEMS-10 LEMS-8 LEMS-10 LEMS-1	LEM-8				•	•	•	•	•	•	•	•	
LEM-10  LEM-12A  LEM-4  LEME-5  LEME-6  LEME-8  LEME-10  LEME-12  LEMS-3  LEMS-3  LEMS-4  LEMS-5  LEMS-6  LEMS-6  LEMS-6  LEMS-8  LEMS-6  LEMS-6  LEMS-6  LEMS-7  LEMS-8  LEMS-10	LEM-8B					•	•	•	•	•	•	•	•
LEM-12A	LEM-10A						•	•	•	•	•	•	•
LEM-12       • • • • • • • • • • • • • • • • • • •	LEM-10					•	•	•	•	•	•	•	•
LEME-4  LEME-5  LEME-6  LEME-8  LEME-10  LEME-12  LEMS-3  LEMS-4  LEMS-5  LEMS-6  LEMS-6  LEMS-6  LEMS-6  LEMS-6  LEMS-8  LEMS-8  LEMS-8  LEMS-8  LEMS-8  LEMS-8  LEMS-8	LEM-12A							•	•	•	•	•	•
LEME-5 LEME-6 LEME-8 LEME-10 LEME-12 LEMS-3 LEMS-4 LEMS-5 LEMS-6 LEMS-6 LEMS-6 LEMS-8 LEMS-8 LEMS-8 LEMS-8 LEMS-8 LEMS-8 LEMS-8 LEMS-10	LEM-12							•	•	•	•	•	•
LEME-6  LEME-10  LEME-12  LEMS-3  LEMS-4  LEMS-5  LEMS-6  LEMS-6  LEMS-6  LEMS-8  LEMS-8  LEMS-8  LEMS-8B  LEMS-10	LEME-4			•	•	•	•	•	•				
LEME-8  LEME-10  LEME-12  LEMS-3  LEMS-4  LEMS-5  LEMS-6  LEMS-6  LEMS-8  LEMS-8  LEMS-8  LEMS-8B  LEMS-10	LEME-5				•	•	•	•	•	•	•		
LEME-10  LEMS-3  LEMS-4  LEMS-5  LEMS-6  LEMS-6B  LEMS-8  LEMS-8B  LEMS-10	LEME-6				•	•	•	•	•	•	•		
LEMS-12	LEME-8				•	•	•	•	•	•	•	•	
LEMS-3  LEMS-4  LEMS-5  LEMS-6  LEMS-6B  LEMS-8B  LEMS-8B  LEMS-10	LEME-10					•	•	•	•	•	•	•	•
LEMS-4       • • • • • • • • • • • • • • • • • • •	LEME-12							•	•	•	•	•	•
LEMS-5       • • • • • • • • • • • • • • • • • • •	LEMS-3	•	•	•	•	•							
LEMS-6       • • • • • • • • • • • • • • • • • • •	LEMS-4			•	•	•	•	•	•				
LEMS-6B	LEMS-5				•	•	•	•	•	•	•		
LEMS-8       ■ </td <td>LEMS-6</td> <td></td> <td></td> <td></td> <td>•</td> <td>•</td> <td>•</td> <td>•</td> <td>•</td> <td>•</td> <td>•</td> <td></td> <td></td>	LEMS-6				•	•	•	•	•	•	•		
LEMS-8B       ●<	LEMS-6B					•	•	•	•	•	•	•	
LEMS-10	LEMS-8					•	•	•	•	•	•	•	
	LEMS-8B						•	•	•	•	•	•	•
LEMS-12	LEMS-10						•	•	•	•	•	•	•
	LEMS-12							•	•	•	•	•	•

• Part number specification

For 12 screw length Lm, select from the sizes marked with 1 in the table.

